

Spec Sheet

60x10mm Replacement Ball Bearing Computer Case Fan w/ TX3 Connector

StarTech ID: FAN6X1TX3



This versatile 60mm fan is an ideal replacement fan for keeping your computer running cool. The fan can be powered through a TX3 connection, and features a dual ball bearing design that ensures reliable cooling and longer fan lifespan.

The fan can be used to replace the fan component of some CPU coolers or mounted to the side panel of a computer case and features a tachometer pin on the TX3 motherboard connector that provides the host system with fan operating status information.

Applications

- Replace a noisy or failed computer case fan
- Install into a computer to increase air flow and cooling

Features

- Dual ball bearing design
- 3-pin connector with tachometer wire
- Includes a 3-pin to 4-pin LP4 Molex adapter

www.startech.com 1 800 265 1844

StarTechcom

Hard-to-find made easy®

Technical Specifications

Warranty	2 Years
Number of Conductors	3
Fan Bearing Type	Ball Bearing
Connector Type(s)	1 - Molex Fan (3 pin; TX3) Female
Fan RPM	4000
Air Flow Rate	15.49 CFM
Noise Level	28 dBA
MTBF	56,609 Hours
Color	Black
Enclosure Type	Plastic
Product Length	2.4 in [60 mm]
Product Width	0.4 in [10 mm]
Product Height	2.4 in [60 mm]
Product Weight	1.3 oz [38 g]
Input Voltage	12 DC
Input Current	160mA
Power Consumption	1.92W
Operating Temperature	-10 to 80
Shipping (Package) Weigh	it 0.2 lb [0.1 kg]
Included in Package	1 - 6cm Case Fan
Included in Package	1 - 3-pin to 4-pin LP4 Molex Adapter Cable

Certifications, Reports and Compatibility



Spec Sheet

www.startech.com 1 800 265 1844