

OVERVIEW



1. Volumn buttons	5. Headphone / microphone combo jack (3.5mm)
2. Action key	6. USB-C (Hi-Speed USB), with charging
3. Card slot	7. Pogo pin connector (4-point)
4. Power button	

- Notes:
- 4-point pogo pin connector is used to connect Smart Charging Station 2 (purchase seperately). The charging station availability varies by country/region.
 - Card slot is for microSD card (WLAN model) or nano-SIM + microSD card (WWAN model)

PERFORMANCE

Processor

Processor**

Processor Name	Cores	Max Frequency	Processor Graphics
Qualcomm® Snapdragon® 680	Kryo 265 Octa-core: 4x A73 + 4x A53	A73@2.4GHz / A53@1.9GHz	Qualcomm® Adreno™ 610 GPU
Qualcomm® Snapdragon® 685	Kryo 265 Octa-core: 4x A73 + 4x A53	A73@2.8GHz / A53@1.9GHz	Qualcomm® Adreno™ 610 GPU

Operating System

Operating System^[1]

Android™ 14 or later

Notes:

[1] For the latest upgrade information, please visit [Android™ Upgrade Matrix](#).

Graphics

Graphics

Qualcomm® Adreno™ 610 GPU

Memory

Max Memory

- 4GB soldered memory, not upgradable
- 6GB soldered memory, not upgradable
- 8GB soldered memory, not upgradable

Memory Type

LPDDR4x

Storage

Storage Support

- 128GB UFS 2.2 on systemboard
- 256GB UFS 2.2 on systemboard
- 64GB UFS 2.2 on systemboard
- microSD card, supports up to 1TB

Removable Storage

Card Reader**

- Nano-SIM + microSD card slot (WWAN models)
- microSD card slot (WLAN models)

Multi-Media

Speakers

4 speakers, optimized with Dolby Atmos®

Microphone

Dual-microphone array

Camera

Front 8.0MP, fixed focus, face unlock

Rear 13.0MP, autofocus, with flashlight

VoiceCall^[1]

- Voice call
- No support

Notes:

[1] Use of Voice call requires cellular data plan. Voice call functionality details may vary based on local operator network,

data and messaging services. Please contact your carriers for details.

Sensor

Vibration Motor

Eccentric Rotating Mass (ERM)

Sensors

- Accelerometer (G) sensor
- Ambient light sensor (ALS)
- Gyroscope sensor
- Hall sensor
- Proximity (P) sensor

Battery

Battery

Integrated Li-Polymer 8600mAh (typical) battery

Max Battery Life^[1]

Video playback: 12 hr
Web browsing: 14 hr

Notes:

[1] All battery life claims are approximate and based on internal testing under optimal laboratory and network conditions. Actual battery performance will vary depending on numerous factors including product configuration and usage, software, operating conditions, wireless functionality, power management settings, screen brightness and other factors. The maximum capacity of the battery will naturally decrease with time and usage.

Power Adapter

Power Adapter

- 10V/2A (20W) AC adapter, 100-240V, 50-60Hz
- No power adapter^[1]

Notes:

[1] For optimal performance, ensure your compatible charger delivers between a minimum of 10 Watts (BC 1.2) required by the product, and a maximum of 20 Watts (USB PD 3.0, QC 3.0) to achieve the fastest charging speed. The Lenovo® 68W USB-C® Wall Charger is recommended for this product. However, other compatible USB PD chargers can also be used.

DESIGN

Display

Display

Size	Resolution	Touch	Type	Brightness	Surface	Aspect Ratio	Contrast Ratio	Color Gamut	Refresh Rate	Viewing Angle (L/R/U/D)
11.45"	2K (2000x1200)	Multi-touch	TDDI	400nits	Anti-fingerprint	15:9	1500:1	72% NTSC	90Hz	80° / 80° / 80° / 80°

Touchscreen

Capacitive-type multi-touch, supports 10-point touch

Input Device

Pen

- Lenovo® Tab Pen Plus, 4096 levels of pressure sensitivity, tilt detection, palm rejection
- No pen (purchase separately)^[1]

Notes:

[1] For details upon pen compatibility, please check the file "Lenovo® Android™ Tablet - Option Compatibility Matrix" from <https://support.lenovo.com/solutions/accs-guide>. Pen availability may vary by country / region.

Mechanical

Dimensions (WxDxH)^[1]

268.7 x 168.96 x 7.15 mm (11.58 x 6.65 x 0.28 inches)

Weight^[2]

Around 520 g (1.15 lbs)

Case Color

Luna grey

Case Material**

- Metal + PMMA
- Metal

Buttons

- Action key
- Power button
- Volume buttons

Notes:

[1] The system dimensions may vary depending on configurations.

[2] The system weight is approximate and based on results in Lenovo® lab, which varies depending on the source of component, variance of the distribution of each component, and manufacturing process. It may not be the exact weight for each specific model.

CONNECTIVITY

Network

WLAN + Bluetooth®

Wi-Fi® 6, 802.11ax 2x2 Wi-Fi® + Bluetooth® 5.3

WWAN

- 4G LTE
- No support

Cellular Bands^[1]

GSM: B2/B3/B5/B8

WCDMA: B1/B2/B5(B6/B19)/B8

FDD LTE: B1/B2/B3(Expanded Band3)/B4/B5(B19)/B7/B8/B20/B26/B28(a+b)

TDD LTE: B38/B40/B41 (Full bandwidth)

NFC

Near Field Communication

Wi-Fi® Direct

Support

Wi-Fi® Display

Support

Location Services**

Models	Location
WLAN models	GPS + GLONASS + Galileo + Beidou
WWAN models	GPS + GLONASS + Galileo + Beidou + A-GPS

Notes:

[1] For WWAN models

Ports

Standard Ports^[1]

- 1x USB-C® (Hi-Speed USB / USB 2.0), with charging
- 1x Headphone / microphone combo jack (3.5mm)

- 1x Card slot
- 1x Pogo pin connector (4-point)^[2]

Notes:

[1] The transfer speed of the ports will vary and, depending on many factors, such as the processing speed of the host device, file attributes, and other factors related to system configuration and your operating environment, will be slower than the theoretical speed.

[2] 4-point pogo pin connector is used to connect Smart Charging Station 2 (purchase separately). The charging station availability varies by country/region.

SERVICE

Warranty

Base Warranty**^[1]

- 1-year carry-in service
- 1-year mail-in service
- 1-year courier service
- 2-year (1-yr battery) carry-in service
- 2-year (1-yr battery) courier service
- 2-year (2-yr battery) courier or carry-in service
- No base warranty

Notes:

[1] For warranty upgrade service, please go to <https://smartfind.lenovo.com/services>. To learn more details of warranty policy, please access <https://support.lenovo.com/warrantylookup/warrantypolicy>.

ACCESSORIES

Bundled Accessories

Bundled Accessories^[1]

- Lenovo® Tab Pen Plus
- None

Notes:

[1] For compatible accessories, please check the file "Lenovo® Android™ Tablet - Option Compatibility Matrix" from <https://support.lenovo.com/solutions/accs-guide>.

OPERATING REQUIREMENTS

Operating Environment

Temperature

Operating: 0°C (32°F) to 40°C (104°F)

CERTIFICATIONS

Green Certifications^[1]

Green Certifications

- ENERGY STAR® 8.0 (only available for TB352FU)
- ErP Lot 6/26
- RoHS compliant

Notes:

[1] The items listed under the "Green Certifications" section may not only refer to certification but also registration or self-declaration. For ESG & regulatory compliance documents, please visit <https://compliance.lenovo.com>.

Other Certifications

Dust and Water Resistant

IP52

Other Certifications

- TÜV Rheinland® Flicker Free
- TÜV Rheinland® Low Blue Light (Hardware Solution)

SOFTWARE**Preinstalled Software****Preinstalled Software^[1]**

- Calculator
- Calendar
- Chrome
- Clock
- Contacts
- Entertainment Space
- Fitbit
- Files by Google
- Find my device
- Gboard
- Gmail
- Google
- Google Assistant
- Google Docs
- Google Drive
- Google Maps
- Google Meet
- Google One
- Google Play Books
- Google Play Games
- Google Sheets
- Google Slides
- Google TV
- Kids Space^[2]
- Lenovo® Freestyle
- MyScript® Calculator 2
- Messages
- Nebo®
- News
- Phone^[3]
- Photos
- Play Store
- Tide
- YouTube
- YouTube Kids
- YouTube Music
- WPS Office

Notes:

[1] Actual application availability varies by country/region.

[2] Books and video content not available in all regions. Video content subject to availability of YouTube Kids app. Books content requires the Play Books app. Availability of apps, books, and video content may change without notice. Google Assistant not available in Google Kids Space. Google Kids Space requires a Google Account for your child. Parental controls require the Family Link app on a supported Android™, Chromebook, or iOS device.

[3] For WWAN models

Additional Software**Additional Software^[1]**

- Access to device management features via SDK
- Additional security patch extensions
- Android™ zero-touch enrollment

- Cloud-based customization & configuration
- Commercial grade SW with limited monetization content^[2]
- Customization management of firmware updates

Notes:

[1] To acquire additional software service, please contact Lenovo® local sales or business partners for the steps of deployment. License/activation fees may be applicable.

[2] Google Mobile Services (GMS) contents are allowed; manufacturer related monetization and push contents are limited.

- Feature with ** means that only one option listed under the feature can be configured on selected models. Please refer to the model configuration for specific information.
- Lenovo reserves the right to change specifications or other product information without notice. Lenovo is not responsible for photographic or typographical errors. LENOVO PROVIDES THIS PUBLICATION “AS IS,” WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING THE IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some jurisdictions do not allow disclaimer of express or implied warranties in certain transactions, therefore this disclaimer may not apply to you.
- The specifications on this page may not be available in all regions, and may be changed or updated without notice.

