

Acer Vero MST Dock M33



Create The Ultimate Workstation

Elevate your workspace with our eco-friendly docking station. Crafted from sustainable materials, it seamlessly integrates with your devices. Compact, stylish, and backed by a one-year International Travelers Warranty (ITW), it's the responsible choice for powerful and sustainable connectivity.

Array of ports

USB Type-A, USB Type-C, HDMI, DisplayPort, RJ45, audio jack: everything you need for your ultimate workstation.

Built-in power supply

Providing up to 100 W of Power Delivery, it ensures efficient charging for your devices, keeping you connected and powered throughout your day.

Sustainable design

Containing PCR (Post-Consumer Recycled) plastic, it merges style and eco-friendliness for a greener workspace.

Advanced functionalities

Improve productivity and simplify management, with compatible Acer laptops.

Input / Output



- | | | | | |
|---------------------------|---------------------------|-------------------------|--------------------------|--------------------|
| 1. Power button | 4. USB-A 10 Gb/s | 7. USB-A 5 Gb/s | 10. Ethernet RJ45 1 Gb/s | 13. HDMI 2.0 |
| 2. LED | 5. USB-A 10 Gb/s (BC 1.2) | 8. Kensington lock slot | 11. DP 1.4 | 14. Host interface |
| 3. 3.5mm audio combo jack | 6. USB-C 10 Gb/s | 9. USB-A 5 Gb/s | 12. DP 1.4 | 15. DC-in jack |

Specifications

Host interface	USB-C	Power adapter	135 W AC
Power Delivery	Up to 100 W with light load, up to 65 W with full load	Security	Kensington lock slot
USB	2x USB-A 5 Gb/s 1x USB-A 10 Gb/s 1x USB-A 10 Gb/s (BC 1.2) 1x USB-C 10 Gb/s	Advanced functionalities	PXE boot MAC address pass-through WOL (MS, S3, S4, S5) Power button and LED mirror
Video	1x HDMI 2.0 2x DP 1.4	Color	Black with Vero signature design
RJ45	1x 1 Gb/s	Dimensions	180(L) x 82(W) x 24.8(H) mm
Audio jack	1x 3.5 mm combo	Weight	232 g
		Warranty	One-year International Travelers Warranty (ITW)

Resolution of Extended Display Matrix

Laptop's USB-C port supports DP 1.4 HBR3 with DSC Enabled	DP1	DP2	HDMI
Single Video Output	Up to 3840x2160@60Hz	Up to 3840x2160@60Hz	Up to 3840x2160@60Hz
Dual Video Output	Up to 3840x2160@60Hz	Up to 3840x2160@60Hz	
	Up to 3840x2160@60Hz		Up to 3840x2160@60Hz
Triple Video Output		Up to 3840x2160@60Hz	Up to 3840x2160@60Hz
	Up to 3840x2160@30Hz	Up to 3840x2160@30Hz	Up to 3840x2160@30Hz
Laptop's USB-C port supports DP 1.4 HBR3	DP1	DP2	HDMI
Single Video Output	Up to 3840x2160@60Hz	Up to 3840x2160@60Hz	Up to 3840x2160@60Hz
Dual Video Output	Up to 2560x1440@60Hz	Up to 2560x1440@60Hz	
	Up to 2560x1440@60Hz		Up to 2560x1440@60Hz
Triple Video Output		Up to 2560x1440@60Hz	Up to 2560x1440@60Hz
	Up to 1920x1080@60Hz	Up to 1920x1080@60Hz	Up to 1920x1080@60Hz
Laptop's USB-C port supports DP 1.2 HBR2	DP1	DP2	HDMI
Single Video Output	Up to 3840x2160@30Hz	Up to 3840x2160@30Hz	Up to 3840x2160@30Hz
Dual Video Output	Up to 1920x1080@60Hz	Up to 1920x1080@60Hz	
	Up to 1920x1080@60Hz		Up to 1920x1080@60Hz
Triple Video Output		Up to 1920x1080@60Hz	Up to 1920x1080@60Hz
	Up to 1600x900@60Hz	Up to 1600x900@60Hz	Up to 1600x900@60Hz

The maximum display numbers, resolutions and refresh rates may vary depending on the specifications and capabilities of your connected host laptops and monitors.

Smart Power Charging Matrix

Total power consumption of downstream devices and docking station	Power Delivery
0~30 W	Up to 100 W
30~45 W	Up to 85 W
45~55 W (max)	Up to 65 W

Power consumption of each port when connect to downstream devices

System consumption	Port 4	Port 5	Port 6	Port 7	Port 9	Port 11	Port 12	Port 13
12.5 W	4.5 W	7.5 W	15 W	4.5 W	4.5 W	1.65 W	1.65 W	1.5 W